



Ellittico 6"x 4" - Coaxial

Program Power	90 W
Rated impedance	4 Ohm
Nominal diameter	Ellittico 6"x 4"- 150 x 96 mm
Sensitivity (2,83V/1m)	91 dB
Voice coil diameter	1 in - 25 mm
Frequency Range	-

SPECIFICATIONS

Nominal Diameter	Ellittico 6" x 4" - 150 x 96 mm
Rated Impedance	4 Ohm
Nominal Power Handling ¹	40 W
Program Power ²	90 W
Sensitivity ³	91 dB
Frequency Range ⁴	-
Minimum Impedance	-
Gasket Material	Steel
Magnet Material	Ferrite
Cone Material	-
Cone Shape	-
Surround	Polyurethane
Suspension	-
Voice Coil Diameter	1 in - 25 mm
Voice Coil Winding Material	-
Voice Coil Length	--
Voice Coil Former Material	Aluminum
Connection type	-
Ferofluid	No
Magnetic Gap Height	4 mm - 0,16 in
Max. Peak to Peak Excursion	-
Efficiency Bandwidth Product EBP	92
Recommended Loading	-
Volume / Tuning frequency	-
Maximum recommended frequency	-

FREQUENCY RESPONSE AND IMPEDANCE CURVE ^{6 7}

T/S PARAMETERS

4 Ohm

Resonance frequency	Fs	159 Hz
DC Resistance	Re	3,5 Ohm
Mechanical Q Factor	Qms	6,8
Electrical Q Factor	Qes	1,73
Total Q Factor	Qts	1,38
BI Factor	BI	2,71 Tm
Effective Moving Mass	Mms	3,63 g
Equivalent Cas air loaded	Vas	2,3 lt (dm ³) - 0,08 cuft
Suspension Compliance	Cms	0,28 mm/N
Effective Piston Diameter	D	99 mm - 3,9 in
Effective piston area	Sd	77 cm ² - 11,94 sq in
Max. Linear Excursion ⁵	Xmax	1,1 mm - 0,04 in
Voice Coil Inductance @ 1kHz	Le	-
Half-space Efficiency	η0	-

MOUNTING AND SHIPPING INFORMATION

Overall Diameter	96x155 mm -
Baffle Cutout Diameter	ell.144x87 mm -
Flange and Gasket Thickness	7 mm - 0,28 in
Total Depth	42,5 mm - 1,67 in
Bolt Circle Diameter	73x123 mm -
Bolt Holes Quantity and Diameter	4 / 5 mm - 0,2 in
Net Weight	0,48 Kg - 1,06 lb
Shipping Units	6 Pcs

NOTES

¹ Nominal power is determined according to AES2-1984 (r2003) standard.

² Program Power is defined as 3 dB greater than the Nominal rating.

³ Sensitivity represents the averaged value of acoustic output as measured on the forward central axis of cone, at distance 1m, when connected to 2,83V sine wave test signal.

⁴ Frequency range is given as the band of frequencies delineated by the lower and upper limits where the output level drops by 10 dB below the rated sensitivity in half space environment.

⁵ Linear Math. Xmax is calculated as (Hvc-Hg)/2 + Hg/4 where Hvc is the coil depth and Hg is the gapdepth.

⁶ 0

⁷ Impedance curve is measured in free air conditions at small signals.