DRIVER

Professional High Frequency Transducer

PART NUMBER **15129038**

The ND950 1.4 is a ultra compact size, high performance, high power handling 4.0-inch diaphragm compression driver with a 1.4 inch exit throat. The high power neodymium magnet guarantee the perfect control of the dome assembly's moving mass. This leads to higher efficiency, better transient response and diminishes high frequency distortion modes. A thin copper ring is precision pressed on to the pole piece in order to modify and lower the inductance characteristics of the magnetic circuit and voice coil providing a controlled extension of the acoustic frequency response. The ND950 1.4 features a 0.05 mm thick pure titanium dome in combination with a high strength Mylar suspension. The voice coil assembly is designed using a high strength, high temperature Kapton® voice coil former and edge wound copper clad aluminium wire. The ND950 1.4 features a 4-slot, optimised geometry, phase plug design. Extended computer assisted mathematical modelling and testing has resulted in a geometry that provides a balanced acoustic performance controlling and lowering air distortion and maximizing output.

Features

- 4.0 inch, Kapton former, edge wound aluminium voice coil
- 1.4" throat
- 280 Watt continuous program power handling
- 110 dB Sensitivity
- 500 Hz –20 KHz Frequency range
- Titanium dome, Polymide surround
- 4 slot phase plug
- The minimum size 4" driver available

Applications

With a wide frequency response range (500 Hz - 20.000 Hz) and 280 Watt power handling, the ND950 1.4 is the ideal driver for heavy duty professional applications.






- 1. Continuos pink noise power ratings are derived from suggested AES standards sending a pink noise signal having a 6 dB crest factor with a high pass filter set at the specified lower limiting frequency for two hours. Continuos program power is a conservative power rating for reproduction of typical audio
- $2. \ Sensitivity \ measurement \ is \ based \ on \ pink \ noise \ signal \ with \ input \ power \ of \ 1 \ watt \ and \ measured \ at \ 1$ meter from the mouth of a horn with a Q of 15 on axis and averaged between 2 and 5 kHz.

3. Frequency range is defined as the measured frequency response -10dB relative to the rat	ed sensitivity

35.5/1.4	mm/inch
8	ohm
280	Watt
140	Watt
110	dB
500 - 20000	Hz
Pure Titanium	
Polymide	
Flat	
8.5 ohm at 3500 Hz	
100/4.0	mm/inch
Edgewound Aluminum	
Kapton	
1 - Outside	
17.6	T · m
2.05	T
4 slot	
Aluminum	
Neodymium	
Copper ring	
	8 280 140 110 500 - 20000 Pure Titanium Polymide Flat 8.5 ohm at 3500 Hz 100/4.0 Edgewound Aluminum Kapton 1 - Outside 17.6 2.05 4 slot Aluminum Neodymium

					_
$-\mathbf{N}\mathbf{A}$	 	200	Info	HIND C	tion
IVI		שוו			

Overall Diameter	146/5.7	mm/inch
Overall Height	60/2.4	mm/inch
Mounting		
4 x 6 mm threaded holes at 180 deg.	101.6/4.0	mm/inch
4 x 6 mm threaded holes at 180 deg. Net Weight	101.6/4.0 3.3/7.1	mm/inch kg/Lbs



Frequency response and electrical impedance curve of the compression driver mounted on HF64 horn with input

500 20.000 20 100 1.000 10.000 20.000