


18HTX100

Triaxials - 18.0 Inches






- 100 dB (LF), 110 dB (MF/HF) sensitivity
- 1600 W continuous program power capacity
- 60°x40° nominal coverage
- 44 18000 Hz response
- FEA optimized horn flare for improved acoustic loading and controlled coverage
- Double silicone spider with optimized compliance
- Aluminium demodulating ring for very low distortion







B&C Speakers s.p.a.









SPECIFICATIONS

| Nominal Diameter | 460.0 mm (18.0 in) |
|-------------------------------|-----------------------|
| Frequency Range | 44.0 - 18000.0 Hz |
| Dispersion Angle ¹ | 60°x40 ° |
| Woofer Cone Treatment TWP | Waterproof Both Sides |
| Magnet Material | Neodymium Ring |
| | |

SPECIFICATIONS LF UNIT

| LF Nominal Impedance | 8 Ω |
|-----------------------------|--------------------------|
| LF Nominal Power Handling | 2 800 W |
| LF Continuous Power Hand | ling ³ 1600 W |
| LF Minimum Impedance | 6.6 Ω |
| LF Sensitivity ⁴ | 100.0 dB |
| LF Voice Coil Diameter | 100.0 mm (3.94 in) |
| LF Winding Material | Aluminium |
| LF Former Material | Glass Fibre |
| LF Winding Depth | 25.1 mm (1.0 in) |
| LF Magnetic Gap Depth | 10.2 mm (0.4 in) |
| LF Flux Density | 1.5 T |

SPECIFICATIONS HF UNIT

| HF Nominal Impedance | 8 Ω |
|-------------------------------------|--------------------------|
| HF Minimum Impedance | 9.0 Ω |
| HF Nominal Power Handlin | ng ⁵ 80 W |
| HF Continuous Power Han | dling ⁶ 160 W |
| HF Sensitivity (1W/1m) ⁷ | 110.0 dB |
| HF Frequency Range | 3.5 - 18.0 kHz |
| HF Recommended Crosso | ver ⁸ 4.0 kHz |
| HF Voice Coil Diameter | 65 mm (2.5 in) |
| HF Winding Material | Aluminium |
| HF Inductance | 0.1 mH |
| Hf diaphragm material | HT Polymer |
| HF Flux Density | 2.14 T |
| HF Magnet Material N | eodymium Inside Slug |

SPECIFICATIONS MF UNIT

| MF Nominal Impedance | 8 Ω |
|--|-----------------|
| MF Minimum Impedance | 6.0 Ω |
| MF Nominal Power Handling ⁹ | 110 W |
| MF Continuous Power Handling | 10 220 W |
| MF Sensitivity (1W/1m) ¹¹ | 110.0 dB |
| MF Frequency Range | 0.5 - 5.5 kHz |
| MF Recommended Crossover ¹² | 2 0.6 kHz |
| MF Voice Coil Diameter | 100 mm (4.0 in) |
| MF Winding Material | Aluminium |
| MF Inductance | 0.21 mH |
| Mf diaphragm material | HT Polymer |
| MF Flux Density | 1.9 T |
| MF Magnet Material | Neodymium Ring |

SERVICE KIT

| HF replacement diaphragm | MMDDCX464HF8 |
|--------------------------|--------------|
| MF replacement diaphragm | MMDDCX464MF8 |

- Included by -6 dB down points.
 2 hours test made with continuous pink noise signal within the range Fs-10Fs. Power calculated on rated minimum impedance. Loudspeaker in free air.
 Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 Applied RMS Voltage is set to 2.83V
 2 hour test made with continuous pink noise signal within the range from the recommended crossover frequency to 20 kHz. Power calculated on rated minimum impedance.
 Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 Appoint test made with continuous pink noise signal within the range from the recommended crossover frequency to 20 kHz. Power calculated on rated minimum impedance.
 Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 Applied RMS Voltage is to ta 2.83V
- 7. 8.
- Applied RMS Voltage is set to 2.83V 12 dB/oct. or higher slope high-pass filter. 2 hour test made with continuous pink noise signal within the range from the recommended crossover frequency to 20 kHz. Power calculated on rated 9.
- minimum impedance.

- minimum impedance.
 Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
 Applied RMS Voltage is set to 2.83V
 12 dB/oct. or higher slope high-pass filter.
 Thiele-Small parameters are measured after a high level 20 Hz sine wave preconditioning test.

PARAMETERS¹³

| | 44.0 Hz |
|---------------------|--|
| Resonance Frequency | 44.0 H2 |
| Re | 5.4 Ω |
| Qes | 0.34 |
| Qms | 6.3 |
| Qts | 0.32 |
| Vas | 173.0 dm ³ (6.11 ft ³) |
| Sd | 1210.0 cm ² (187.55 in ²) |
| ηo | 4.3 % |
| Xmax | ± 10.0 mm |
| Xvar | ± 13.0 mm |
| Mms | 158.5 g |
| BI | 26.3 Txm |
| Le | 1.16 mH |
| EBP | 129 Hz |
| | |

MOUNTING AND SHIPPING INFO

| Overall Diameter | 460.0 mm (18.11 in) |
|--|---------------------|
| Bolt Circle Diameter | 440.0 mm (17.32 in) |
| Baffle Cutout Diameter | 423.0 mm (16.65 in) |
| Depth | 299.0 mm (11.77 in) |
| Flange and Gasket Thickness ^{16.0} mm (0.63 in) | |
| Net Weight | 12.4 kg (27.34 lb) |

Via Poggiomoro, 1 - Loc. Vallina, 50012 Bagno a Ripoli (FI) - ITALY - Tel. +39 055 65721 - Fax +39 055 6572312 - mail@bcspeakers.com