

## **CD-10Fe/N** COMPRESSION DRIVER

### **KEY FEATURES**

- 1" (25 mm) high frequency compression driver
- Sensitivity 109 dB (1W / 1m)
- Improved moving assembly mechanical coupling for excellent power handling capabilities
- PM-4 polymer diaphragm with higher surface tension energy
- Ultra lightweight edgewound aluminium ribbon voice coil
- Aluminium cover
- Ferrite magnet

## TECHNICAL SPECIFICATIONS


Throat diameter Rated impedance	25 mm	1 in 8 Ω
Minimum impedance		5 Ω
D.C. resistance		4,3 Ω
Power capacity*	70 WAES above 1,2 kHz	
Program power	140 W above 1,2 kHz	
Sensitivity**	109 dB 1W / 1m @ Z <sub>N</sub>	
	coupled to	D-164
Frequency range	0,7 - 19 kHz	
Recommended crossover	1,2 kHz or higher	
	(12 dB/oct min.)	
Voice coil diameter	44,4 mm	1,75 in
Magnetic assembly weight	1,2 kg	2,86 lb
Flux density		1,65 T
BI factor		6,6 N/A

#### **MOUNTING INFORMATION**

Overall diameter Depth	100 mm 62 mm	3,94 in 2,44 in	
Mounting	Three M5 threaded holes, 7	120° apart	
	on 57 mm (2,24 in) diameter circle		
	Two M5 threaded holes, 7	180° apart	
	on 76,2 mm (3 in) diameter circle		
Net weight	1,3 kg	2,86 lb	
Shipping weight	1,4 kg	3,10 lb	



### **DIMENSION DRAWINGS**




Notes:


\* The power capaticity is determined according to AES2-1984 (r2003) standard. Program power is defined as the transducer's ability to handle normal music program material.

\*\* Sensitivity was measured at 1m distance, on axis, with 1W input, averaged in the range 1 - 7 kHz.



# **CD-10Fe/N** COMPRESSION DRIVER





## beyma JJ

Polígono Industrial Moncada II • C/. Pont Sec, 1c • 46113 MONCADA - Valencia (Spain) • Tel.: (34) 96 130 13 75 • Fax: (34) 96 130 15 07 • http://www.beyma.com • E-mail: beyma@beyma.com •