

Model No: XT25TG30-04 Product Line: Vifa Rev: 1.0 Last Update: 2015-10-22 21:15:31


**Driver Specification Sheet** 

## Product Description

This member of the XT tweeter family utilizes two Tymphany technologies to deliver exceptional sound quality: the ring radiator patent, and the central waveguide patent. This model features a 4 ohm 25mm voice coil, mounted in a ferrite magnet motor. The tweeter also features a rear chamber to create extended low frequency response. The faceplate features recessed mounting holes which minimizes reflections off of mounting screws.



## **Mechanical Drawing**



## Specifications

Minimum Impedance Zmin   Voice Coil Inductance Le   Resonant Frequency Fs   Mechanical Q Factor Qms   Electrical Q Factor Qes   Total Q Factor Qts	Ohms mH Hz 0.54	3.47 0.01 436.13 2.5	7.5% 15%	Moving Mass Suspension Compliance Effective Cone diameter Effective Piston Area Effective Volume	Mms Cms D Sd Vas	g um/N cm cm^2	0.4 366.5 3.24 8.2
Resonant Frequency Fs   Mechanical Q Factor Qms   Electrical Q Factor Qes	Hz	436.13 2.5	15%	Effective Cone diameter Effective Piston Area	D Sd	cm	3.24 8.2
Mechanical Q Factor Qms Electrical Q Factor Qes		2.5	15%	Effective Piston Area			8.2
Electrical Q Factor Qes	0.54					cm^2	
	0.54			Effective Volume	Vas	1	0.04
Total O Eactor Ote						L	0.04
		0.44		Motor Force Factor	BL	Tm	2.36
Ratio Fs/Qts F	Fs/Qts	988.97		Motor Efficiency Factor	ß	(T*M^2)/Ohms	1.9
Half Space Sensitivity @2.83V db@2.83V/1M	dB	90.84	+/- 1.0db	Voice coil former Material	VCfm		ASV
Half Space Sensitivity @1W/1M db@1W/1M	dB	87.2	+/- 1.0db	Voice coil inner diameter	VCd	mm	25.76
Gap Height Gh	mm	3		Rated Noise Power	Р	W	110
Maximum Linear Excursion Xmax	mm	0.5		Test Spectrum Bandwidth	400hz - 20khz		
Ferrofluid Type FF				Driver Size	Inch	25 mm	
Driver Mass Kg	0.5						

## **Frequency and Impedance Response**

